

MASTECH®

Build to Precision

Digital Multimeter MS8251B

تلفن تهران (دفتر مرکزی) : ۰۲۱ - ۴۷ ۶۲ ۷۰ ۱۰

دورنگار : ۰۲۱ - ۴۳ ۸۵ ۹۶ ۱۰

تلفن دفتر مشهد : ۰۵۱-۳۷۱۳۸۱۰۵-۶

دورنگار دفتر مشهد : ۰۵۱-۳۷۱۳۷۳۳۳۷



مشخصات فنی مولتی متر مدل MS8251B

- جریان: AC/DC ۱۰۰۰ A
- ولتاژ: AC – 1000V DC ۵۰۰۰ V
- مقاومت الکتریکی: ۶۶۰ M ohm
- ظرفیت خازن: ۶۶۰ MF
- فرکانس: ۶۶۰ MHz
- دما: ۱۰۰۰ C ~
- اندازه گیری ماکزیمم مقادیر (peakhold)
- اتصال کوتاه – بیزر – تست دیود
- دارای حافظه مینیمم ماکسیمم – بدنه ضربه گیر
- همراه با کیف حمل و پرابهای مربوطه

- Auto ranging Digital Multimeter with True RMS and Low Impedance Input Mode Mastech MS-8251B
- Auto Range
- REL (Relative Measurement)
- True RMS (True Root Mean Square Measurement)
- Low Z (Low Impedance Input Mode)
- NCV (Non-Contact Voltage Detector)
- Measures DC/AC Voltage and Current, Resistance, Capacitance, Frequency , Duty Cycle And Temperature
- Diode Check and Continuity Test
- MAX / MIN
- Data Hold
- APO (Auto Power Off)
- LBD (Low Battery Display)
- Display Back Light

- Quick Details
- Place of Origin: Guangdong China
- Brand Name: MASTECH
- Model Number: MS8251B
- Measuring Current Range: 10A
- Measuring Voltage Range: 1000V
- Measuring Resistance Range: 66M Ω
- Measuring Capacitance Range: 66mF
- Operating Temperature: -10~50°C
- Dimensions: 175x85x52mm/6.9x3.3x2.1"
- Color: Green
- Specifications
- 1.6600 counts LCD Display
- 2. Test DC Voltage, AC Voltage ,DC Current, AC Current Resistance,Capacitance,Frequency,Relative

جهت خرید و اطلاعات محصول بر روی اندرس زیر کلیک کنید:

[/http://www.seeanco.com/professional-digital-multimeter-ms8251b-models](http://www.seeanco.com/professional-digital-multimeter-ms8251b-models)

